

LOUD button

When you need an instant "boost" in the volume, a simple push of the "LOUD" button gives you full volume immediately. In addition, holding the "LOUD" button mutes the audio output.

Noise cancelling microphone

The sub-microphone on the rear panel inverts phase and cancels out ambient noise from the main microphone. As a result, the IC-M35 reduces the affect of background noise (particularly trebly noise) from the transmitted signal and makes it easier to catch voice communication.

Automatic volume adjustment

When in an engine room or high noise environment, the sub-microphone detects the ambient noise and the IC-M35 automatically increases the volume output to suit the surrounding environment.

Low power consumption

Although the IC-M35 delivers a high 6W*1 RF output and 700mW audio output, its current saving circuit offers a practical 8 hours*2 of operating time with the supplied 980mAh Lithium-Ion battery pack.

- *1 Depending on version.
- *2 Typical operation with Tx (Hi): Rx: standby=5:5:90

Large buttons and slim dimensions

Thanks to the large, easy-to-operate buttons, the IC-M35 provides intuitive operation. A pinched-waist slender body makes it easy to hold and carry the radio, and is surprisingly compact for a floating radio.

Other features

- · Waterproof construction equivalent to IPX7 (1m depth for 30 minutes)
- Dual/Tri-watch functions
- 4-step battery life indicator
- Auto scan function
- Instant access to Ch 16 or programmable call channel

SPECIFICATIONS

GENERAL

 Frequency range 156.000-161.450MHz 156.000-163.425MHz

 Usable channels : INT, USA* channels; 70 programmable channels

(* Depending on version) Type of emission : 16K0G3E (FM)

• Current drain (at 7.4V DC)

6W output 5W output 1.5A typical 1.3A typical AF max.

Internal speaker External speaker Power save

300mA typical 200mA typical 10mA typical • Operating temperature range: -15°C to +55°C

 Antenna impedance : 50Ω (STUD) • Dimensions (W×H×D) : 62×139.5×43 mm (projections not included)

: 295g (with BP-252, MB-109

and antenna)

Weight (approx.)

TRANSMITTER

6/1W* Output power (Hi/Low)

2/1W (with alkaline battery) Australia version 5/1W * German version 1/0.5W

 Max. frequency deviation: ±5.0kHz Frequency error : ± 1.5kHz Spurious emissions : 0.25uW Adjacent channel power : 70dB

• Audio harmonic distortion : Less than 10% (at 60% dev.)

 Residual modulation : 40dB

RECEIVER

 Sensitivity (20dB SINAD) : -2dBµ emf typical

 Squelch sensitivity -6dBµ emf typical (threshold) Adjacent Ch. selectivity : 70dB 70dB Spurious response

* Australia version Intermodulation rejection 68dB Hum and noise ratio : 40dB

Measurements made in accordance with EN301-178-2. All stated specifications are subject to change without notice or obligation.

Audio output power (at 10% distortion)

Internal speaker 700mW typical (with a 16Ω load) External speaker 200mW (with an 8Ω load)

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810 F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4	I, II
Solar Radiation	505.4	I
Rain	506.4	I, III
Humidity	507.4	-
Salt fog	509.4	-
Dust	510.4	I
Immersion	512.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C. -D and -E

| Ingress Protection Standard | Dust & Water | IP57 (Dust-protection and waterproof protection)

Supplied accessories

Battery pack, BP-252
 Battery charger, BC-173

Belt clip, MB-109 AC adapter, BC-147*

· Battery case, BP-251 (UK version only)

(* Not supplied depending on version.)

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.



BP-251 BATTERY CASE Battery case for LR03 (AAA)×5 alkaline cells. Output power: 2W.

BP-252 Li-lon BATTERY PACK 7.4V, 950 mAh (min.) 980mAh (typ.). Provides 8 hours operating time (approx.).

(Typical operation with Tx (Hi): Rx: standby=5:5:90)



BC-173 DESKTOP CHARGER + **BC-147***1 AC ADAPTER Charges the battery pack, BP-252,

ICOM Inc. 1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

in 10 hours (approx.).

Rapidly charges the battery pack. BP-252, in 2 hours (approx.) BC-145/BC-147SA for 120V AC. SE for 230V AC. SV for 240V AC. BC-145SUK for 230V AC.



HM-165 SPEAKER-MICROPHONE Waterproof construction equivalent to IPX7 (1 m depth for 30 min.).



MB-109 BELT CLIP Alligator type. Same as supplied



FA-SC58V ANTENNA Soft flexible antenna. Same as supplied.

Count on us!

Please note: The noise cancellation can produce little or no effect in some conditions depending on type of noise, or the position and distance between the noise source and the microphone, etc. The noise cancellation does not work when an optional external speaker-microphone is connected.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia, Japan and/or other countries.

+ BC-145*1 AC ADAPTER

Icom America Inc. Icom New Zealand 2380 116th Avenue NE, Bellevue, WA 98004, U.S.A. Phone: +1 (425) 454-8155 Fax : +1 (425) 454-1509

URL: http://www.icomamerica.com Icom Canada

E-mail: sales@icomamerica.com

Glenwood Centre #150-6165 Highway 17. Delta, B.C., V4K 5B8, Canada Phone: +1 (604) 952-4266 Fax: +1 (604) 952-0090 E-mail: info@icomcanada.com URL: http://www.icomcanada.com

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road, Clayton, VIC 3168 Australia Phone: +61 (03) 9549 7500 Fax: +61 (03) 9549 7505 URL: http://www.icom.net.au

Auckland, New Zealand Auckland, New Zealand Phone: +64 (09) 274 4062 Fax : +64 (09) 274 4708 E-mail: inquiries@icom.co.nz URL: http://www.icom.co.nz

Icom (Europe) GmbH

Communication Equipment Auf der Krautweide 24 65812 Bad Soden am Taunus, Germany Phone: +49 (6196) 76685-0 Fax : +49 (6196) 76685-50 E-mail : info@icomeurope.com

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer Bajos A 08174, Sant Cugat del Valles,

Barcelona, Spain Phone: +34 (93) 590 26 70 Fax: +34 (93) 589 04 46 E-mail: icom@icomspain.com URL: http://www.icomspain.com

Icom (UK) Ltd.

Blacksole House, Altira Park, Herne Bay, Kent, CT6 6GZ, U.K. Phone: +44 (01227) 741741 Fax : +44 (01227) 741742 E-mail: info@icomuk.co.uk : http://www.icomuk.co.uk

Icom France s.a.s.

Zac de la Plaine. 1 Rue Brindejonc des Moulinais, BP 45804 31505 Toulouse Cedex 5, France Phone: +33 (5) 61 36 03 03 Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: http://www.icom-france.com

Icom Polska

81-850 Sopot, ul. 3 Maja 54, Poland Phone: +48 (58) 550 7135 Fax : +48 (58) 551 0484 E-mail: icompolska@icompolska.com.pl URL: http://www.icompolska.com.pl Your local distributor/dealer:

www.icom.co.jp/world



NETHERLANDS | Roermond Tel. +31 (0)475-327390 www.classicinternational.eu

GERMANY | Mönchengladbach Tel. +49 (0)2166-33061 www.classicinternational.eu

09HS001C © 2009–2011 Icom Inc.