

seatec-5

MARINE TRANSCEIVER

VHF FM MARINE TRANSCEIVER

156-162 MHz 5W

PC PROGRAMMABLE

5W RF !
1500mAh
NI-MH BATTERY
AND CHARGER
INCLUDED !

seatec-5
VHF FM HANDHELD
MARINE TRANSCEIVER
156-162 MHz 5W



5W MOSFET
CIRCUIT DESIGN

VHF FM marine handheld transceiver, fully PC programmable, with built-in high power 5W MOSFET transmitter. Only 6 pcs AA batteries required. Backlighted 4-lines 1.8" LCD Display. Adjustable transmitter RF power level (5W/2W/1W). 100 memory channels and 120 private channels programmable. Manual or auto squelch, Dual Watch and Triple Watch, SCAN, S/R/F Digital Signal Meter and a lot more functions. Complete with 1500mAh Ni-MH rechargeable batteries for up to 10 hours operating time and 230VAC charger. Professional electronic and mechanical design.

- Fastpath to the rescue channel 16
- 120 Private Channels programmable
- International channels, USA channels and Canadian channels
- Meteo weather channels
- 4-lines 1.8" extra-wide backlighted LCD display
- 6-digit full frequency readout
- 100 Memory Channels
- Keypad Lock
- Manual or Auto Squelch
- Dual Watch function / Triple Watch function
- Adjustable 3-level Transmitter Power (5W/2W/1W)
- Advanced MOSFET Transmitter Circuit Design
- Channel / Memory Scan / Priority Channel
- ATIS/ALERT functions
- 4-bar Battery Level Meter / 10-bar digital S/R/F Meter
- External Earset-Microphone Jack / Wall Charger Jack
- Dimensions : L66 X D38 x H146 mm (main body)
- Weight : gr. 370 (including batteries)
- PC programmable (with optional programming kit)
- 1500mAh Ni-MH batteries and 230VAC adaptor charger included

100 MEMORIES
120 PRIVATE CHANNELS
ATIS/ALERT

CONTENTS OF THE PACKAGE :

- 1 x Handheld Transceiver
- 1 x 230VAC Adaptor Charger
- 6 x 1.2V 1500mAh Ni-MH Battery
- 1 x Belt Clip
- 1 x User Manual



RoHS
2002/95/EC